User's Guide 3229/3421

CASIO

F-1

ENGLISH

Congratulations upon your selection of this CASIO watch.

Important!

. This manual provides a brief overview of your watch.

For a full Operation Guide and Q&A information about this product, go to the website below.

http://world.casio.com/manual/wat/



Ε

Configuring Time and Date Settings

To set the time and date

- 1. Press (A) while in the Timekeeping Mode. The seconds digits flash on the display because they are selected.
- 2. Press \circledcirc to change the selection in the following sequence.




3. While the seconds digits are selected (flashing), press (B) to reset the seconds to "00". If you press (B) while the seconds count is in the range of 30 to 59, the seconds are reset to "00" and 1 is added to the minutes. If the seconds count is in the range of 00 to 29, the minutes count is unchanged.

- 4. While any other digits (besides seconds) are selected (flashing), press (B) to increase the number. Holding down (B) changes the number at high speed.
 To switch between the 12-hour and 24-hour formats, press (D) while
 - some digits are flashing.
- 5. After you set the time and date, press (A) to return to the Timekeeping Mode.

Mode Selection and Operations

• Press © to change the mode

• After you perform an operation in any mode, pressing © returns to the Timekeeping Mode



E-4 E-5

Specifications

Accuracy at normal temperature: ±15 seconds a month

Timekeeping: Hour, minutes, seconds, pm (PM), month, day, the day of the week Time system: Switchable between 12-hour and 24-hour formats Calendar system: Auto-calendar pre-programmed from the year 2000 to 2099

Alarm: Multi-function alarm, hourly time signal

Countdown Timer Measuring unit: 1 second Input range: from 1 second to 24 hours Other: Auto-repeat function

Stopwatch

Measuring units: 1/100 second (for the first 60 minutes) 1 second (after 60 minutes)
Measuring capacity: 23 hours, 59 minutes, 59 seconds
Measuring modes: Elapsed time, split time and two finishes

Illumination: EL (electro-luminescent) backlight

Battery: One lithium battery (Type: CR2016)
Approximately 2 years on type CR2016 (Assuming 3.5 seconds light operation and 20 seconds alarm operation per day)
Note: Frequent use of the backlight shortens the battery life noted above.

Specifications are subject to change without notice.